
Output Transformer (Output to Line)

Primary Impedance: 75ohm


Secondary Minimum Load Impedance: 75ohm (1:1), 300ohm (1:2), 600ohm (1:3)




To use the 2503-L in place of the EA2503, follow this table:

2503-L	EA2503	
Red	Gray	
Pink	Blue	
Yellow	Yellow	
Orange	Red	
Black	Violet	
Gray	Green	
White	Orange	
Violet	Brown	

Flat Mount with standoffs, PCB cut-out, or vertically with Keystone #708 threaded "L" bracket.





Designed by: Classic Audio		Classic
Drawn: 3/14/2015		Audio roducts
Scale: 1:1	capi-gear.com	Inc

2503-L Audio Output Transformer

